



## ZTX110

### ZTX110 Signal Generator Extender

Part-No.: 1425.7609.02

#### Product Description

##### Key Features:

- Full-band frequency range WR10 (75-110 GHz)
- High output power
- Convenient handling
- Test port adapters
- Multi position housing for on-wafer and waveguide based measurements

##### Accessories/Options:

- Antennas
- Fixed attenuators



Technical Specifications	
RF Frequency [GHz]	75 - 110
Output Power [dBm (typ)]	+14
RF Output Port	WR10 (UG387/UM)
RF Output VSWR (typ.)	1.7:1
Multipl. Factor	6
RF Input Frequency [GHz]	12.5 - 18.34
RF Input Port	2.92 mm female
RF Input Power [dBm]	+ 7
Input Damage Level [dBm]	> +15
Harmonics [dBc (typ.)]	< -20
Subharmonics [dBc (typ.)]	< -20
In-Band spurious [dBc (typ.)]	< -20
Operating Temperature	+18 °C to +30 °C
Dimensions (WxHxD) [mm] plus feet high (adjustable from 13 to 23mm, depending on positioning)	220 x 70 x 110
Weight [kg]	< 1.9 kg



**Typical Performance**

