



SHM 140-170
Subharmonic Mixer narrowband 140-170 GHz
Part-No.: 02000038



Technical Specifications

RF Frequency [GHz]	140 - 170
RF Port	WR6 (UG387/UM)
LO Frequency [GHz]	70 - 85
LO Port	WR13 (UG387/UM)
LO Power [dBm]	4
IF Frequency	10 MHz - 20 GHz
IF Port	2.92 mm male/female
Conversion Loss (DSB)	5
Noise Temperature	500
Max. RF Power	0 dBm
Max. LO Power	10 dBm
Max. Case Temperature	+45 °C